



Portable multi-channel input/output device

The U 951 is a portable device that transmits data in multiple channels. Digital signal transmission is stable and accurate. And support Shuttle driver, compatible with AudioExpert. Customizable input (software optional), output 1 or 0.

General

U951 parameters	
DI Number of input channels	16
DI Number of input channels	16
working voltage	5V
Dimension(mm)	96*33*140
Working temperature	-20°C~50°C
Interface type	Pluggable terminal

General features

- Digital signal input and output function
- 16 DIO channels
- Customizable digital waveform output
- Small, portable device without external power supply

MegaSig reserves the right to change specifications and accessories without notice.



www.megasig.com

Shenzhen MegaSig Measurement & Control Technology Co.,Ltd

Tel: 0755-8950.8393 Fax: 0755-8950.8392

Sales email: sale@megasig.com

Technical support email: support@megasig.com

Address: Room 1002, Unit 2, Building 1, Hongxing Chuangzhi Plaza, Guangming District, Shenzhen, China